



シャトルリング貯線長チャート



シャトルリング幅 電線サイズ 貯線長		S8 & B8 ローテーター					
		8 mm	10 mm	12 mm	15 mm	17 mm	20 mm
AWG NO.16	1.290mm		18.29	23.47	30.18	45.42	73.15
AWG NO.17	1.151mm		23.16	29.57	38.1	56.69	92.05
AWG NO.18	1.024mm	14.94	28.96	37.19	48.16	71.93	116.43
AWG NO.19	0.912mm	18.59	36.88	47.24	60.66	90.53	146.61
AWG NO.20	0.813mm	23.47	46.02	59.13	76.2	114	184.4
AWG NO.21	0.724mm	29.57	62.18	74.98	96.01	143.56	232.56
AWG NO.22	0.643mm	37.49	74.98	94.79	121.92	182.27	295.05
AWG NO.23	0.574mm	47.24	92.35	119.18	152.7	228.6	370.03
AWG NO.24	0.511mm	59.13	116.74	149.96	192.94	288.34	466.95
AWG NO.25	0.455mm	75.29	147.22	189.28	243.23	363.63	588.87
AWG NO.26	0.404mm	95.1	186.84	240.18	308.76	461.16	747.06
AWG NO.27	0.361mm	119.79	234.09	300.53	386.49	577.6	935.43
AWG NO.28	0.320mm	151.79	296.27	382.83	491.95	734.87	1190.6

貯線長単位: M
UNIT OF WIRE LENGTH: M

