



TOROID SHUTTLE WIRE CAPACITY CHART

シャトルリング貯線長チャート



シャトルリング幅 電線サイズ 貯線長		B4 ベルトタイプ								B6 ベルトタイプ					
		2.4 mm	2.5 mm	2.8 mm	3.4 mm	4.7 mm	6.3 mm	7.9 mm	9.5 mm	4.7 mm	6.3 mm	7.9 mm	9.5 mm	12.7 mm	15.6 mm
AWG NO.19	0.912mm							3.96	7.01			5.79	10.67	17.68	
AWG NO.20	0.813mm				0.91	1.52	3.66	4.88	8.53	2.44	5.49	7.32	13.11	21.95	
AWG NO.21	0.724mm				1.22	2.13	4.27	6.1	10.67	3.35	6.71	9.14	16.15	27.13	
AWG NO.22	0.643mm				1.52	2.44	5.49	7.62	13.11	3.66	8.23	11.58	19.81	33.83	
AWG NO.23	0.574mm			1.22	1.83	3.05	6.71	9.14	16.46	4.57	10.06	14.02	24.69	42.06	63.09
AWG NO.24	0.511mm		1.22	1.52	2.44	3.96	8.23	11.58	20.42	6.1	12.5	17.37	30.78	51.82	77.72
AWG NO.25	0.455mm	1.22	1.52	2.13	3.05	4.88	10.36	14.33	25.3	7.32	15.54	21.64	38.1	64.31	96.32
AWG NO.26	0.404mm	1.52	1.83	2.44	3.66	6.1	12.8	17.68	31.09	9.14	19.2	26.52	46.63	65.84	98.76
AWG NO.27	0.361mm	1.83	2.13	3.05	4.57	7.32	15.85	21.95	38.71	10.97	23.77	32.92	58.22	98.76	148.13
AWG NO.28	0.320mm	2.13	2.74	3.66	5.49	9.14	19.81	27.13	47.85	13.72	29.87	40.84	71.93	121.92	182.88
AWG NO.29	0.287mm	3.05	3.35	4.57	7.01	11.28	24.32	33.83	59.44	17.07	36.58	50.9	89.31	151.18	226.77
AWG NO.30	0.254mm	3.66	4.27	5.79	8.53	14.02	30.48	41.76	73.76	21.03	45.72	62.79	110.64	186.84	280.11
AWG NO.31	0.226mm	4.27	5.49	7.32	10.67	17.37	37.8	51.82	91.44	26.21	56.69	77.72	137.16	231.34	347.47
AWG NO.32	0.203mm	5.49	6.71	8.84	13.41	21.64	46.63	64.62	113.39	32.61	70.1	96.93	170.08	286.51	429.77
AWG NO.33	0.180mm	7.01	8.23	10.97	16.46	26.82	57.61			40.23	86.56	119.79	210.31	354.48	531.88
AWG NO.34	0.160mm	8.53	10.06	13.72	20.42	33.53	71.93			50.29	107.9	148.44	260.3	438.91	658.37
AWG NO.35	0.142mm	10.67	12.5	17.07	25.3	41.45	89			62.18	133.5	183.49	322.17	543.15	814.73
AWG NO.36	0.127mm									76.81	165.2	227.38	398.98	672.08	1005.8
AWG NO.37	0.114mm									95.1	204.52	281.33	493.78	832.1	1219.2
AWG NO.38	0.102mm									117.96	252.98	348.08	611.12		

貯線長単位: M

UNIT OF WIRE LENGTH: M

シャトルリング幅 電線サイズ 貯線長		S4 スライダータイプ				S6 スライダータイプ					
		4.7 mm	6.3 mm	7.9 mm	9.5 mm	4.7 mm	6.3 mm	7.9 mm	9.5 mm	12.7 mm	15.6 mm
AWG NO.24	0.511mm			11.58	20.42	6.1	12.5	17.37	30.78	51.82	77.72
AWG NO.25	0.455mm			14.63	25.6	7.32	15.54	21.64	38.1	64.31	96.32
AWG NO.26	0.404mm	6.1	12.8	17.98	31.7	9.14	19.2	26.52	46.63	65.84	98.76
AWG NO.27	0.361mm	7.32	15.85	22.25	39.01	10.97	23.77	32.92	58.22	98.76	148.13
AWG NO.28	0.320mm	9.14	19.81	27.43	48.46	13.72	29.87	40.84	71.93	121.92	182.88
AWG NO.29	0.287mm	11.58	24.38	34.44	60.35	17.07	36.58	50.9	89.31	151.18	226.77
AWG NO.30	0.254mm	14.33	30.48	42.67	74.68	21.03	45.72	62.79	110.64	186.84	280.11
AWG NO.31	0.226mm	17.68	37.49	52.73	92.66	26.21	56.69	77.72	137.16	231.34	347.47
AWG NO.32	0.203mm	21.95	46.63	65.53	114.91	32.61	70.1	96.93	170.08	286.51	429.77
AWG NO.33	0.180mm	27.13	57.91	81.38	142.65	40.23	86.56	119.79	210.31	354.48	531.88
AWG NO.34	0.160mm	33.53	71.63	100.58	176.48	50.29	107.9	148.44	260.3	438.91	658.37
AWG NO.35	0.142mm	41.45	89	124.97	219.15	62.18	133.5	183.49	322.17	543.15	814.73
AWG NO.36	0.127mm	51.51	110.34	154.84	271.58	76.81	165.2	227.38	298.98	672.08	1005.8
AWG NO.37	0.114mm	63.7	136.86	192.02	336.8	95.1	204.52	281.33	493.78	832.1	1219.2
AWG NO.38	0.102mm	79.25	169.47	238.05	417.58	117.96	252.98	348.08	611.12		
AWG NO.39	0.089mm	98.15	210.31	295.35	518.16	146	313.03				
AWG NO.40	0.079mm	121.62	260.6	365.76	642.52	180.44	387.71				
AWG NO.41	0.064mm	150.88	323.09	454.15	796.75						
AWG NO.42	0.056mm	187.45	400.81	562.97	987.55						
AWG NO.43	0.051mm	232.56	497.13	697.99	1225.3						
AWG NO.44	0.046mm	288.34	616.31								

貯線長単位: M

UNIT OF WIRE LENGTH: M